

Remote Control User Manual

Battery

This remote requires one 12-volt battery to be installed. Sold separately. Please make sure polarities match according to diagram located inside battery compartment (Fig. 2).

Pairing Instructions

1. Turn power to fan off either by wall switch or circuit breaker.
2. Return power to the fan and within 30 seconds,
3. Press the LEARN key (Fig. 2, 7), located inside battery compartment. The indicator light will flash. If paired successfully, fan will turn on low speed and light will be on.

Product functions (See Fig. 1 & 2)

- ☐ Keys: (1), (2), (3). When pressed, these keys adjust the fan's speed.
- ☐ Key: (4). When pressed, this key turns off the fan's motor.
- ☐ Key (5): Press and release immediately to turn on/off the light; Press and hold to cycle light dimming.
- ☐ Toggle switch D/CFL (6): Slide the switch according to the light bulb(s) installed.
 - ☐ D – Set the light for use with incandescent bulbs; allows light on, off and dimming functionality.
 - ☐ CFL – Set the light for use with compact fluorescent bulb(s) (CFL); allows only light on and off functionality.

⚠ ATTENTION: Must not use with un-dimmable loading (CFL) when transmitter is in D (incandescent dimming) mode. It will shorten DFL working life substantially and may damage the controller.

⚠ CAUTION: The battery will weaken with age and should be replaced before leaking takes place as this will damage the transmitter. Dispose of used battery properly. Keep the battery out of reach of children.

Installing the wall mount bracket

- ☐ For transmitter placement, locate wall bracket in a convenient location. Use two screws to install wall bracket on the wall. Then hang transmitter in it carefully; aligning the tab from the wall mount bracket to be inserted into the slot on the back of the remote (See Fig 3.).

NOTE:

The frequency of our RC-92T remote is 315MHz, and it can replace the FCC ID/MODEL: A25-TX013/A25TX013, A25-TX001-R1/A25TX001R1, ZJF-RT01A/ZJFRT01A, A25-TX005R /A25TX005R

Please note, the frequency of below remote FCC ID is 304MHz, and it can not be replaced: KUJCE10716/TR258B, KUJST18003, A25-TX00I/A25TX00I, KUJCE10512, A25-TX00I/RRTX00I

WARNING

For help, please contact Replacement Remotes customer support of the store you purchased, or mail to: Support@ceilingfanremote.com.

